



Three Phase Squirrel Cage Induction Motor

Motor type TE Q3HSFA 132S2C

Electrical Data

RATED VALUES							STARTING VALUES				BREAKDOWN	EFFICIENCY			Eff. CLASS
VOLTAGE	POWER		SPEED	CURRENT	TORQUE	Cos ϕ	CURRENT IA/IN		TORQUE MA/MN		TORQUE Mk/Mn	%			IEC 60034-30-1
V	kW	Hz	rpm	A	Nm	4/4	Y	D	Y	D	Nm	4/4	3/4	2/4	IE
400/690	5,5	50	2920	10,5/6,1	18,06	0,86	3,9	11,56	1,2	3,73	5,1	IE3-89,2%	89	87,2	IE3
460/795	6,3	60	3520	10,1/5,8	17,09	0,87	3,7	11,21	1,2	3,54	4,9				

Mechanical Data

Bearing DE	6208-ZZ	Color	RAL 7031
Bearing NDE	6206-ZZ	Motor protection	PTC
Lubricants	Shell Gadus S2 V100Q2	Method of cooling	IC 411 (TEFC)
Condensation drain hole	No	Terminal box position	Top
External earthing terminal	Yes	Material of terminal box	Aluminium
Vibration class	A	Terminal plate thread	M5
Insulation class	F	Cable gland	1xM25
Duty type	S1	Clamping range	18-25 mm
Direction of rotation	Clockwise	Mounting type	IM B5 (FA)
Housing material	Aluminium		
Type of balancing	Half Key		

Environmental Data

Others

Ambient Temperature	-20/+40 °C	Type of protection	IP55
Altitude above sea level	1000 m	Sound Pressure Level 50/60Hz dBA	69
		Moment of Inertia (kg.mm2)	0,0077198
		Standard	IEC 60034-1
		Weight (Kg)	36,2

*Lubrication:

Closed type (ZZ) roller bearings are being used.

These types of roller bearings do not require maintenance since they are lubricated with the type of lubricant specified by the manufacturer.

Roller bearings should be replaced after 20,000 hours of operation (approx. 2-5 years of use) due to the specified operation temperature, vibration level and shaft loads.