


## FLOW-BUS – Modbus CABLE PARTS


### FLOW-BUS - Modbus RJ45 connector

| Symbol                                                                                    | Description                                      | Lenght | Part number |
|-------------------------------------------------------------------------------------------|--------------------------------------------------|--------|-------------|
|          | patch cable (standard RJ45 S(F)TP)               | 0,5 m  | 7.03.236    |
|                                                                                           |                                                  | 3 m    | 7.03.238    |
|                                                                                           |                                                  | 5 m    | 7.03.239    |
|                                                                                           |                                                  | 10 m   | 7.03.318    |
|                                                                                           |                                                  | 0,15 m | 7.03.542    |
|          | patch cable (standard RJ45 / loose end)          | 3 m    | 7.03.544    |
|          | RJ45 Y-adaptor                                   | 0,3 m  | 7.03.241    |
|          | RJ45 Multi-port adaptor (5 port RJ45)            | 0,3 m  | 7.03.299    |
|  (red)   | RJ45 bus begin-terminator                        |        | 7.03.297    |
|  (black) | RJ45 bus end-terminator                          |        | 7.03.298    |
|          | RJ45 power isolator (only dat cores put through) |        | 1.09.239    |


### FLOW-BUS - Modbus M12 A-code connector

|                                                                                     |                             |       |          |
|-------------------------------------------------------------------------------------|-----------------------------|-------|----------|
|  | M12 connector 5pol.male     |       | 1.09.379 |
|  | M12 connector 5pol.female   |       | 1.09.380 |
|  | M12 begin terminator female |       | 7.03.515 |
|  | M12 end terminator male     |       | 7.03.321 |
|  | M12 Y-adaptor               |       | 7.03.319 |
|  | FLOW-BUS M12 cable          | 0,3 m | 7.03.322 |
|                                                                                     |                             | 3 m   | 7.03.323 |
|  | FLOW-BUS M12 power isolator |       | 7.03.350 |


### ONLY FLOW-BUS M12 / RJ45 \* \*the RJ45 connector is not IP65

|                                                                                     |                                       |       |          |
|-------------------------------------------------------------------------------------|---------------------------------------|-------|----------|
|  | FLOW-BUS M12 Female / RJ45 Cable      | 3 m   | 7.03.347 |
|  | FLOW-BUS M12 Male / RJ45 Cable        | 3 m   | 7.03.358 |
|  | FLOW-BUS M12 Female to RJ45 Y-adaptor | 0,3 m | 7.03.357 |
|  | FLOW-BUS cable                        |       | 1.15.162 |

## RS232/FLOW-BUS

| Symbol                                                                            | Description                            | Lenght | Part number |
|-----------------------------------------------------------------------------------|----------------------------------------|--------|-------------|
|  | RS232/FLOW-BUS interface box 32bit     |        | 7.09.128    |
|  | RS232 male/female 9-pin D for 7.09.128 | 1,8 m  | 7.03.234    |
|  | cable RS232 T-part DB9 MBC II          | 3 m    | 7.03.366    |
|  | cable RS232 T-part 8DIN                | 3 m    | 7.03.444    |
|  | cable RS232 DB9/DB9 MBC II             | 3 m    | 7.03.367    |
|  | cable RS232 DB9 to 8DIN                | 3 m    | 7.03.340    |

## RS232 to USB convertor\* \*the convertor is **not** IP65

|                                                                                    |                          |  |          |
|------------------------------------------------------------------------------------|--------------------------|--|----------|
|  | RS232 male DB9 to USB2.0 |  | 9.09.122 |
|------------------------------------------------------------------------------------|--------------------------|--|----------|